

Guide de configuration pour un accès à internet par câble : CableCom

Ce guide se base sur le modèle DIR-635 pour illustrer la configuration essentielle des routeurs DIR, permettant l'accès à internet chez CableCom. En effet elle est applicable à tous les routeurs DIR étant donné qu'ils possèdent tous un menu semblable.

Laissez le modem-câble éteints pendant environ 2 minutes. Reliez par câble réseau le modem-câble et le routeur en utilisant le port WAN de ce dernier et le routeur et l'ordinateur à l'aide d'un autre câble réseau, en utilisant cette fois-ci l'un des ports LAN du routeur. Mettez le modem-câble sous tension, de même que le routeur.

La configuration par défaut du routeur est adaptée à une connexion au net par câble. Donc après la réalisation des raccordements décrits ci-dessus, vous devriez normalement avoir accès au net. De ce fait la configuration suivante n'est en réalité pas nécessaire, mais peut être utile si vous rencontrez des problèmes

1. Accédez au menu de configuration du routeur à partir d'un navigateur internet, par exemple : Internet Explorer v6 ou supérieur, Firefox, ... en tapant son adresse IP dans la barre d'adresse du navigateur internet. Son adresse IP par défaut est : <http://192.168.0.1>
2. Par défaut le nom d'utilisateur (**User Name**) est : „admin“ et l'appareil n'a besoin d'aucun mot de passe (**Password**). Laissez donc ce champ vide et cliquez sur „Log In“.

Product Page: DIR-635 Hardware Version: A1 Firmware Version: 1.07

D-Link

LOGIN

Log in to the router:

User Name : Admin

Password :

WIRELESS



- Si nécessaire cliquez en haut, sur l'onglet „Setup“, ensuite à gauche sur „Internet“, puis en dessous sur le bouton „Manual Configure“.

Product Page: DIR-635 Hardware Version: A1 Firmware Version: 1.07

D-Link

DIR-635 // **SETUP** ADVANCED TOOLS STATUS SUPPORT

INTERNET CONNECTION

There are two ways to set up your Internet connection: you can use the Web-based Internet Connection Setup Wizard, or you can manually configure the connection.

INTERNET CONNECTION WIZARD

If you would like to utilize our easy to use Web-based Wizards to assist you in connecting your new D-Link Systems Router to the Internet, as well as configure the Wireless settings, click on the Setup Wizard button below.

[Setup Wizard](#)

Note: Before launching these wizards, please make sure you have followed all steps outlined in the Quick Installation Guide included in the package.

MANUAL INTERNET CONNECTION OPTIONS

If you would like to configure the Internet settings of your new D-Link Systems Router manually, then click on the Manual Configure button below.

[Manual Configure](#)

Helpful Hints...

If you are new to networking and have never configured a router before, click on **Setup Wizard** and the router will guide you through a few simple steps to get your network up and running.

If you consider yourself an advanced user and have configured a router before, click **Manual Configure** to input all the settings manually.

[More...](#)

WIRELESS

- Sous „Internet Connection Type“, dans la liste déroulante : „My Internet Connection is“ choisissez, si nécessaire „Dynamic IP (DHCP)“.

INTERNET CONNECTION TYPE

Choose the mode to be used by the router to connect to the Internet.

My Internet Connection is:

- Static IP
- Dynamic IP (DHCP)**
- PPPoE (Username / Password)
- PPTP (Username / Password)
- L2TP (Username / Password)
- BigPond (Australia)

DYNAMIC IP (DHCP) INTERNET CONNECTION

Use this Internet connection type if you didn't provide you with IP Address information and

Host Name:

Use Unicasting: (compatibility for some DHCP Servers)

Primary DNS Server:

Secondary DNS Server:

MTU: (bytes) MTU default = 1500

MAC Address:

[Clone Your PC's MAC Address](#)

WIRELESS

accessing the Internet through the router, double check any settings you have entered on this page and verify them with your ISP if needed.

[More...](#)

5. Vous pouvez entrer n'importe quoi dans le champ „Host Name“ ou le laisser vide.

Product Page: DIR-635 Hardware Version: A1 Firmware Version: 1.07

D-Link

DIR-635 // SETUP ADVANCED TOOLS STATUS SUPPORT

INTERNET
WIRELESS SETTINGS
NETWORK SETTINGS

WAN

Internet Connection

Use this section to configure your Internet Connection type. There are several connection types to choose from: Static IP, DHCP, PPPoE, PPTP, L2TP, and BigPond. If you are unsure of your connection method, please contact your Internet Service Provider.

Note: If using the PPPoE option, you will need to remove or disable any PPPoE client software on your computers.

INTERNET CONNECTION TYPE

Choose the mode to be used by the router to connect to the Internet.

My Internet Connection is:

DYNAMIC IP (DHCP) INTERNET CONNECTION TYPE :

Use this Internet connection type if your Internet Service Provider (ISP) didn't provide you with IP Address information and/or a username and password.

Host Name:

Use Unicasting: (compatibility for some DHCP Servers)

Primary DNS Server:

Secondary DNS Server:

MTU: (bytes) MTU default = 1500

MAC Address:

WIRELESS

Helpful Hints...

When configuring the router to access the Internet, be sure to choose the correct **Internet Connection Type** from the drop down menu. If you are unsure of which option to choose, contact your **Internet Service Provider (ISP)**.

If you are having trouble accessing the Internet through the router, double check any settings you have entered on this page and verify them with your ISP if needed.

[More...](#)

6. Ne modifiez pas Les champs „Primary DNS Server“ et „Secondary DNS Server“.
7. Dans „MTU“ entrez la valeur 1500.
8. Cliquez sur le bouton „Clone Your PC's MAC Address“.
9. Cliquez en haut sur le bouton „Save Settings“ pour sauvegarder la configuration.
10. Une Fenêtre s'affichera, cliquez sur „OK“ pour confirmer.

L'appareil redémarre : Un compte à rebours s'affiche, laissez le temps s'écouler.



Contacter D-Link

Informations utiles à fournir

Avant de nous contacter par téléphone ou par mail, veuillez apprêter les informations suivantes :

L'appareil D-Link : (les informations nécessaires se trouvent généralement sur l'appareil) :

- Numéro de Modèle
- Numéro de Série (S/N)
- Révision du Hardware (H/W-Ver.)
- Version du Firmware (F/W-Ver.), le cas échéant la version du dernier Firmware installée
- Date exacte d'achat (pour toutes réclamations)
- Votre complète Adresse postale (Pout toutes réclamations)

L'Ordinateur :

- Le Système d'exploitation et la version du Service Pack Installé. Ex. : Windows XP, Service Pack 2. Précisez, si vous possédez une version 64 Bit.

Comment nous contacter ?

Par E-mail

Ecrivez nous à l'adresse : support@dlink.de . N'oubliez pas de donner les informations utiles mentionnées ci-dessus.

Par Téléphone

Allemagne : **+49 (0) 1805 – 27 87** (0,14€ / Min à partir du fixe (Deutsche Telekom))

Autriche : **+43 (0) 820 – 48 00 84** (0,116€ / Min à partir du fixe en Autriche)

Suisse : **+41 (0) 848 – 33 11 00** (0,11CHF / Min à partir du fixe en Suisse)

Premium-Hotlines

Allemagne : **+49 (0) 9001 – 47 57 67** (1,75€ / Min à partir du fixe (Deutsche Telekom))

Autriche : **+43 (0) 900 – 48 48 47** (1,81€ / Min à partir du fixe en Autriche)

Suisse : **+41 (0) 900 – 47 57 67** (2,50CHF / Min à partir du fixe en Suisse)

