

Schedules (erstellen von Zeitplänen)

1. Greifen Sie per Webbrowser auf die Konfiguration des DGL-4100/4300 zu.
Die Standard Adresse ist <http://192.168.0.1>

2 Im Auslieferungszustand ist auf die Konfiguration kein Passwort gesetzt. Wählen Sie als „User Name“ Admin und lassen Sie das „Password“ Feld leer und klicken Sie auf „Log In“. Sollten Sie bereits ein Passwort vergeben haben logen Sie Sich bitte mit Ihrem Passwort ein.

3. Klicken Sie oben auf „Tools“ und dann links auf „Schedules“.

The screenshot shows the configuration interface for a D-Link Gaming Router, specifically the 'Schedules' page under the 'TOOLS' menu. The browser window title is 'D-Link Gaming Router : Tools / Schedules - Microsoft Internet Explorer'. The address bar shows 'http://192.168.0.1/Tools_Schedules.html'. The page features a navigation bar with 'BASIC', 'ADVANCED', 'TOOLS', 'STATUS', and 'HELP'. A left sidebar lists various configuration categories, with 'SCHEDULES' selected. The main content area is titled 'SCHEDULES' and includes a description: 'The Schedule configuration option is used to manage schedule rules for various firewall and parental control features.' Below this are two buttons: 'Save Settings' and 'Don't Save Settings'. The 'ADD SCHEDULE RULE' section contains a form with the following fields: 'Name' (text input), 'Day(s)' (radio buttons for 'All Week' and 'Select Day(s)', with 'Select Day(s)' selected), 'All Day - 24 hrs' (checkbox), 'Start Time' (hour:minute, 12 hour time), and 'End Time' (hour:minute, 12 hour time). There are 'Save' and 'Clear' buttons at the bottom of the form. Below the form is a 'SCHEDULE RULES LIST' table with columns for 'Name', 'Day(s)', and 'Time Frame'. The footer of the page reads 'Copyright © 2004-2006 D-Link Systems, Inc.'.

4. Geben Sie dem einen Namen.

5. Soll der Zeitplan jeden Tag rund um die Uhr (24 Stunden) gültig sein, wählen Sie bei „Day(s)“ „All Week“ aus.

Bei „All Day – 24 hrs“ setzen Sie einen Haken.

Klicken Sie dann auf „Save“ um den Zeitplan zu übernehmen.

Klicken Sie dann oben auf „Save Settings“ um die vorgenommenen Einstellungen zu übernehmen.

The screenshot shows the D-Link Gaming Router configuration interface in a Microsoft Internet Explorer browser window. The browser title is "D-Link Gaming Router : Tools / Schedules - Microsoft Internet Explorer". The address bar shows "http://192.168.0.1/Tools_Schedules.html". The page features a navigation menu with tabs for "BASIC", "ADVANCED", "TOOLS", "STATUS", and "HELP". The "TOOLS" tab is selected, and a sidebar on the left lists various configuration options, with "SCHEDULES" highlighted. The main content area is titled "SCHEDULES" and includes a description: "The Schedule configuration option is used to manage schedule rules for various firewall and parental control features." Below this are two buttons: "Save Settings" and "Don't Save Settings". The "ADD SCHEDULE RULE" section contains a form with the following fields and options: "Name" (text input with "Regell" entered), "Day(s)" (radio buttons for "All Week" (selected) and "Select Day(s)"), "All Day - 24 hrs" (checkbox, checked), "Start Time" (time selection fields: 0:00 AM), and "End Time" (time selection fields: 0:00 AM). "Save" and "Clear" buttons are at the bottom of the form. Below the form is a "SCHEDULE RULES LIST" table with columns for "Name", "Day(s)", and "Time Frame". The footer of the page reads "Copyright © 2004-2006 D-Link Systems, Inc.".

6. Soll ein Zeitplan an bestimmten Tagen gelten, wählen Sie bei „Day(s)“ „Select Day(s)“ aus und haken die betreffenden Tage an.

Soll der Zeitplan zu bestimmten Uhrzeiten gelten darf „All Day – 24 hrs“ nicht angehakt sein.

Tragen Sie darunter die Zeitspanne ein, z.B.

Start Time = 8 : 0 AM

End Time = 7 : 0 PM

Bedeutet dann eine Zeitspanne von 8 Uhr Vormittags (morgens) bis 7 Uhr Nachmittags (abends).

Klicken Sie dann oben auf „Save Settings“ um die vorgenommenen Einstellungen zu übernehmen.

The screenshot shows the D-Link Gaming Router web interface in Microsoft Internet Explorer. The browser address bar shows `http://192.168.0.1/Tools_Schedules.html`. The interface has a top navigation bar with 'BASIC', 'ADVANCED', 'TOOLS', 'STATUS', and 'HELP'. The 'TOOLS' section is expanded, showing a sidebar with 'TOOLS' selected and a main content area for 'SCHEDULES'. The 'SCHEDULES' section contains a description, 'Save Settings' and 'Don't Save Settings' buttons, and an 'ADD SCHEDULE RULE' form. The form has the following fields: 'Name' (text input with 'Regel1'), 'Day(s)' (radio buttons for 'All Week' and 'Select Day(s)', with 'Select Day(s)' selected), 'All Day - 24 hrs' (checkbox), 'Start Time' (time selector with '8 : 0 AM'), and 'End Time' (time selector with '7 : 0 PM'). Below the form is a 'SCHEDULE RULES LIST' table with columns for 'Name', 'Day(s)', and 'Time Frame'. The footer of the page reads 'Copyright © 2004-2006 D-Link Systems, Inc.'.

7. Klicken Sie auf „Reboot the Device“ um den DGL-4100/4300 neu zu starten.

