

Product Highlights

SuperSpeed USB 3.0

USB 3.0 technology allows you to transfer files up to 10 times faster than with USB 2.0, and charge your smartphones and tablets

Compatible With Your Devices

Backward compatibility with USB 2.0 and 1.1 ensures that you can connect all your USB devices, whether old or new

Convenient Compact Design

Its small size allows you to slip it easily into your laptop bag or lay unobtrusively on your desktop surface



DUB-1340

4-Port SuperSpeed USB 3.0 Charger Hub

Features

Added Connectivity

- Four USB 3.0 ports
- Backward compatible with USB 2.0 and USB 1.1 devices

SuperSpeed USB 3.0

- High-speed file transfers at 5 Gbps - almost ten times faster than USB 2.0
- Four downstream ports support SuperSpeed, Hi-Speed (480 Mbps), low (1.5 Mbps) and full-speed (12 Mbps) USB transfers

Efficient Charging

- Able to charge four smartphones or tablets (including iPads) simultaneously
- Downloadable software¹ allows devices to charge while data is being transferred

Easy To Use

- Plug and Play
- Sync-n-go minimizes user wait-time
- Works on Windows, Mac, and Linux computers

Sleek and Portable Design

- Slim and lightweight, for portability without losing functionality
- Fits easily in your laptop, backpack or briefcase

D-Link's DUB-1340 4-Port SuperSpeed USB 3.0 Charger Hub provides an easy way to add four USB 3.0 ports to your notebook or desktop computer. USB 3.0 lets you reach SuperSpeed data transfer rates of 5 Gbps, while also supporting high, full, and low-speed transfer rates. The four USB 3.0 ports are backward compatible, so all your devices can be plugged in. Compact with a sleek, black design, you can take it with you wherever you go.

Transfer Large Files Faster Than Ever

Use the DUB-1340 to instantaneously share files with colleagues, friends and family. The DUB-1340 can transfer data at 5 Gbps, or ten times faster than USB 2.0. SuperSpeed transfer rates make it faster than ever to transfer music, HD movies, photo albums, and other large files—making waiting for file transfers a thing of the past.

Connect and Charge More Devices

With the DUB-1340, you can conveniently add more USB 3.0 ports to any computer. Now you can connect up to 4 more USB peripheral devices, such as smart phones, tablets, external hard drives, flash drives, and printers – to your notebook or desktop computer. Use the 4-Port SuperSpeed USB 3.0 Charger Hub as a charging station to charge up to as many as four iPads or save time by transferring data from one or more flash drives at lightning speeds, all at the same time!¹

Compatible with All Your Devices

The DUB-1340 is backward compatible with your USB 2.0 and 1.1 devices. Featuring four ports; SuperSpeed, Hi-Speed, full, and low-speed USB transfers are supported, ensuring your older devices are still relevant. The DUB-1340 supports previous USB standard devices, while providing USB 3.0 high speed transfers to your newer devices, making the DUB-1340 an ideal portable USB hub for home and office use.

Super Simple and Convenient

Simply plug in the DUB-1340 to any Mac or PC. It's that easy - no drivers or software installation required. Featuring sync-n-go, the DUB-1340 lets your computer quickly recognize the hub so you can immediately get up to four additional USB devices running in no time.

Take it with You Anywhere

The DUB-1340 is designed to fit into any notebook bag, as its compact size lets you bring it with you anywhere. Experience the freedom and convenience of portability and versatility with the DUB-1340 4-Port SuperSpeed USB 3.0 Charger Hub.

Back View



Side View



Technical Specifications

General

Standards	<ul style="list-style-type: none"> • USB specification version 3.0 (data rates of up to 5 Gbps) • OHCI • xHCI 	<ul style="list-style-type: none"> • USB 1.1 • USB 2.0 • USB 3.0
Interfaces	<ul style="list-style-type: none"> • 4 downstream USB Type A (female) ports 	<ul style="list-style-type: none"> • 1 upstream USB Type Micro-B (female) port
Connectivity Rules	<ul style="list-style-type: none"> • Up to 127 devices • Up to five cascaded hubs 	<ul style="list-style-type: none"> • Maximum cable length between each hub: 3 m
System Requirements	<ul style="list-style-type: none"> • Windows 10 / 8 / Win 8 RT / 7 / Vista / XP • Mac OS 	<ul style="list-style-type: none"> • Linux

Physical

Dimensions	<ul style="list-style-type: none"> • 75 x 51 x 14.5 mm (2.9 x 2.0 x 0.57 inches)
Weight	<ul style="list-style-type: none"> • 60 grams (2.12 ounces)
Power	<ul style="list-style-type: none"> • External power adapter 5 V / 4 A • Supplied: Maximum 2.4 A per port² (with external AC adapter)
Temperature	<ul style="list-style-type: none"> • Operating: 0 to 50 °C (32 to 122 °F) • Storage: -20 to 60 °C (-4 to 140 °F)
Operating Humidity	<ul style="list-style-type: none"> • 0% to 80% non-condensing
Certifications	<ul style="list-style-type: none"> • CE • FCC

DUB-1340 4-Port SuperSpeed USB 3.0 Charger Hub

Order Information	
<i>Part Number</i>	<i>Description</i>
DUB-1340	4-Port SuperSpeed USB 3.0 Charger Hub

¹ Windows operating system required.

² Maximum total 16 W.

Updated 2016/03/17