

## ADSL2/+ Modem

### High-Speed Internet Connection

- Up to 24Mbps Download Speed
- ADSL2/ADSL2+ Standard Compliance
- 10/100Mbps Ethernet Interface to Host

#### FEATURES

##### High-Speed ADSL Access

- ADSL: G.992.1 G.dmt, G.992.2 G.lite, ANSI T1.413 Issue 2 (Full Rate DMT Over Analog POTS) Annex B
- ADSL2: G.992.3 (G.dmt.bis) Annex B
- ADSL2+: G.992.5 Annex B
- G.994.1 G.hs Auto-Negotiation of Different ADSL Flavors

##### Host Interface

- 10/100BASE-TX Ethernet Port With Auto MDI/MDIX
- O.S.-Independent

##### Easy Setup/Flexible Management

- Local/Remote Management Through Telnet
- Factory Reset Button
- TFTP Firmware Upgradeable

The DSL-380T ADSL2/+ modem is a high-speed broadband modem for home and office use. Featuring the latest ADSL2/+ standards, this modem provides speeds of up to 24Mbps downstream and 1Mbps upstream (ADSL2+), or 12Mbps downstream and 1Mbps upstream (ADSL2). The modem auto-negotiates the best modulation scheme, using the G.hs (handshake) protocol.

The DSL-380T ADSL2/+ modem support "always on" connections to eliminate dial-up wait time and busy signals. Web surfing and your e-mail are instantly available, any time. Like any ADSL modem, it lets you access the Internet using your existing phone lines, without interfering with your voice phone service. You can talk on the phone and surf the net at the same time. Along with instant connectivity, you can surf the Internet at very high speeds.

With high-speed connections (depending on the rate that you subscribe with your Internet service provider), you won't have to wait for downloads of graphic-intensive web pages. These speeds are also ideal for on-line audio/video streams, Internet games, VoIP phone communication applications and transfers of large files over the Internet.

Installation is quick and simple. You connect the modem to any PC with an available Ethernet port, or to a router to share high-speed Internet access with a group of users at home or the office.



## Technical Specifications

### Device Interfaces

- RJ-11 ADSL port
- RJ-45 10/100BASE-TX Ethernet port with auto MDI/MDIX
- Factory reset button

### ADSL Standards

- ADSL standards: ANSI T1.413 Issue 2, ITU G.992.1 (G.dmt) Annex B, ITU G.992.2 (G.lite) Annex B
- ADSL2 standards: ITU G.992.3 (G.dmt.bis) Annex B, ITU G.992.4 (G.lite.bis) Annex B
- ADSL2+ standards: ITU G.992.5 Annex B
- Auto-handshake: ITU G.994.1 (G.hs)

### ADSL Data Rates

- G.dmt: 8Mbps downstream, 832Kbps upstream
- G.lite: 1.5Mbps downstream, 512Kbps upstream
- ADSL2: 12Mbps downstream, 1Mbps upstream
- ADSL2+: 24Mbps downstream, 1Mbps upstream

### ATM & PPP Protocols

- ATM Adaptation Layer Type 5 (AAL5)
- Bridged or routed Ethernet encapsulation
- VC and LLC based multiplexing
- PPP over Ethernet (PPPoE)
- PPP over ATM (RFC 2364)
- Classical IP over ATM (RFC 1577)
- OAM F4/F5

### Management/Configuration

- Telnet server for remote/local management
- TFTP firmware upgrade

### Diagnostic LEDs

- Power
- Status
- ADSL Link/Activity
- Ethernet Link/Activity

## Physical & Environmental

### Power Input

Through 9VAC 1A external power adapter

### Power Consumption

9 watts (max.)

### Dimensions

142 x 108 x 31 mm

### Operating Temperature

0° to 40°C

### Storage Temperature

-20° to 70 °C

### Operating Humidity

5% to 95% non-condensing

### Emission

CE

### Safety

CSA International



## D-Link Worldwide Offices

<b>U.S.A.</b>	TEL: 1-800-326-1688	FAX: 1-866-743-4905	<b>Luxemburg</b>	TEL: 32-(0)2-517-7111	FAX: 32-(0)2-517-6500
<b>Canada</b>	TEL: 1-905-8295033	FAX: 1-905-8295223	<b>Poland</b>	TEL: 48-(0)-22-583-92-75	FAX: 48-(0)-22-583-92-76
<b>Europe (U. K.)</b>	TEL: 44-20-8731-5555	FAX: 44-20-8731-5511	<b>Hungary</b>	TEL: 36-(0)-1-461-30-00	FAX: 36-(0)-1-461-30-09
<b>Germany</b>	TEL: 49-6196-77990	FAX: 49-6196-7799300	<b>Singapore</b>	TEL: 65-6774-6233	FAX: 65-6774-6322
<b>France</b>	TEL: 33-1-30238688	FAX: 33-1-30238689	<b>Australia</b>	TEL: 61-2-8899-1800	FAX: 61-2-8899-1868
<b>Netherlands</b>	TEL: 31-10-282-1445	FAX: 31-10-282-1331	<b>India</b>	TEL: 91-022-26526696	FAX: 91-022-26528914
<b>Belgium</b>	TEL: 32(0)2-517-7111	FAX: 32(0)2-517-6500	<b>Middle East (Dubai)</b>	TEL: 971-4-3916480	FAX: 971-4-3908881
<b>Italy</b>	TEL: 39-02-2900-0676	FAX: 39-02-2900-1723	<b>Turkey</b>	TEL: 90-212-289-56-59	FAX: 90-212-289-76-06
<b>Sweden</b>	TEL: 46-(0)8564-61900	FAX: 46-(0)8564-61901	<b>Egypt</b>	TEL: 202-414-4295	FAX: 202-415-6704
<b>Denmark</b>	TEL: 45-43-969040	FAX: 45-43-424347	<b>Israel</b>	TEL: 972-9-9715700	FAX: 972-9-9715601
<b>Norway</b>	TEL: 47-99-300-100	FAX: 47-22-309580	<b>LatinAmerica</b>	TEL: 56-2-232-3185	FAX: 56-2-232-0923
<b>Finland</b>	TEL: 358-9-2707 5080	FAX: 358-9-2707-5081	<b>Brazil</b>	TEL: 55-11-218-59300	FAX: 55-11-218-59322
<b>Spain</b>	TEL: 34-93-4090770	FAX: 34-93-4910795	<b>South Africa</b>	TEL: 27-12-665-2165	FAX: 27-12-665-2186
<b>Portugal</b>	TEL: 351-21-8688493		<b>Russia</b>	TEL: 7-095-744-0099	FAX: 7-095-744-0099 #350
<b>Czech Republic</b>	TEL: 420-(603)-276-589		<b>China</b>	TEL: 86-10-58635800	FAX: 86-10-58635799
<b>Switzerland</b>	TEL: 41-(0)-1-832-11-00	FAX: 41(0)-1-832-11-01	<b>Taiwan</b>	TEL: 886-2-6600-0123	FAX: 886-2-6600-8168
<b>Greece</b>	TEL: 30-210-9914 512	FAX: 30-210-9916902	<b>Headquarters</b>	TEL: 886-2-6600-0123	FAX: 886-2-6600-9898