







# **Bluetooth 1.1 Adapter for PC**

The DBT-120 is a versatile Bluetooth adapter for Windows-based PCs. Low-power and low-cost, this adapter simply plugs to any USB port on your PC to deliver wireless Personal Area Network connection for your PC. Very compact and lightweight, this adapter, about half the size of your finger, lets you easily talk and send data/images wirelessly to your PDAs, mobile phones, printers, laptop computers and other emeringing electronic devices.

## Bluetooth 1.1 Standard

Adhering to Bluetooth 1.1 standard, the DBT-120 supports wireless data transfers of 723Kbps at ranges up to 10 meters or 33 feet. This capability allows you to establish an automatic wireless connection at a decent speed within a convenient range between your computer and your PDA, mobile phone and other devices.

## **Wireless Connection**

As a new technology for wireless connectivity, the DBT-120 lets you connect to a wide variety of devices without long cables trailing all over the place. Using a radio-based link with integrated antenna, the DBT-120 connects different devices together, giving you more freedom to roam.

## Data Encryption Security

Security is an issue when data is transmitted without the wires. In the air, transmitted data can be easily intercepted if not well protected by a security scheme. The DBT-120 provides the necessary security, using the enhanced 128-bit data encryption on any Bluetooth communication.

## Simple Installation

The DBT-120 plug-and-play feature makes installation on your computer simple and easy. With Bluetooth software provided and easy-to-understand instructions, this adapter lets you experience true wireless connectivity and enhanced compatibility with Bluetooth enabled devices.

## Features

- Connects PC with Bluetooth-enabled devices
- Seamless Wireless Personal Area Nework (PAN) connectivity
- Bluetooth 1.1 compliant
- Plugs to PC's USB port (USB 1.1 compliant)
- 723Kbps transfer rate

- Built-in antenna with wireless range of up to 10 meters/33 feet
- Allows connection to 1 or more Bluetooth-enabled devices simultaneously
- Plug-and-play installation

## **Technical Specifications**

## **Bluetooth Adapter**

## **General Functions**

- Supports up to 7 slave devices

### **Standards**

- Bluetooth 1.1
- USB 1.1

## **Transfer Rates**

- 723 Kbps Asymmetrical max.
- 433.9 Kbps Symmetrical max.

## **Data Encryption**

128-bit

## **Receiver Sensitivity**

-80 dBm typical across passband under high interference Environments

## **RF Technology**

Frequency Hopping Spread Spectrum

## **RF-Wireless Frequency**

- 2400 to 2483.5 MHz for USA/Europe/Japan
- 2446.5 to 2483.5 MHz France

### Range

Up to 10 meters (33 feet) peer-to-peer

## Physical & Environmental

## **Operating Voltage**

5VDC +/- 10%

## **Power Consumption**

- Maximum 62mA in transmit mode
- Maximum 43mA in receive mode
- Maximum 259uA in sleep mode

## **Dimensions**

47 x 19 x 10 mm

## Weight

78 grams (0.18 lb)

## **Operating Temperature**

 $-10^{\circ} \sim 55^{\circ} \text{ C } (14^{\circ} \sim 131^{\circ} \text{ F})$ 

## **Storage Temperature**

 $-20^{\circ} \sim 75^{\circ} \text{C} (-4^{\circ} \sim 167^{\circ} \text{F})$ 

Up to 95%, non-condensing

## **Emission Certification**

- FCC Class B
- CE Class B

## Software

## O.S. Driver Support

Windows 98SE, 2000, ME, XP





## **Ordering Information**

**DBT-120** 

Bluetooth 1.1 Adapter for PC (1-meter USB 1.1 A-to-B cable provided)



Europe Germany France Benelux Italy Iberia Sweden Norway Denmark Finland Singapore Australia Japan China India Egypt UΔE Turkey Israel Chile South Africa Russia Taiwan D-Link Corp. TEL: 1-949-788-0805 TEL: 1-905-8295033 TEL: 44-20-8731-5555 TEL: 33-1-30238688 TEL: 31-10-2045740 TEL: 39-2-2900-0676 TEL: 34-93-4090770 TEL: 46-(0)8564-61900 TEL: 47-22-309075 TEL: 358-9-2707-5080 TEL: 65-6774-6233 TEL: 61-2-8899-1800 TEL: 81-3-5434-9678 TEL: 86-10-8518-2533 TEL: 91-22-652-6696 TEL: 202-62-44615 TEL: 971-4-3916480 TEL: 90-212-335-2525 TEL: 972-9-9715700 TEL: 56-2-232-3185 TEL: 55-11-3094-2910 TEL: 27(0)1266-52165

TEL: 886-2-2910-2626

FAX: 1-949-753-7033 FAX: 1-905-8295095 FAX: 44-20-8731-5511 FAX: 33-1-30238689 FAX: 31-10-2045880 FAX: 39-2-2900-1723 FAX: 34-93-4910795 FAX: 46-(0)8564-61901 FAX: 47-22-309085 FAX: 358-9-2707-5081 FAX: 65-6774-6322 FAX: 61-2-8899-1868 FAX: 81-3-5434-9868 FAX: 86-10-8518-2250 FAX: 91-22-652-8914 FAX: 202-62-44583 FAX: 971-4-3908881 FAX: 90-212-335-2500 FAX: 972-9-971-5601 FAX: 56-2-232-0923 FAX: 55-11-3094-2921 FAX: 27(0)1266-52186 FAX: 7-095-737-3390 FAX: 886-2-2910-1515 TEL: 886-2-2916-1600 FAX: 886-2-2914-6299

