DCS-6100LH Web recovery instructions

1.Rest DCS-6100LH or let it go into AP mode：

（1）Power on device(about 30 seconds)， device led blinking orange.

（2）Hold reset button for more than 5 seconds, wait until LED turn into blinking red from blinking orange then release reset button.

Whole process：Blinking orange-->Hold reset button(LED become solid red) -->Hold reset button for more than 5 seconds until it become blink red then release reset button.

It goes into recover AP mode.

2.Upgrade steps：

（1）Search SSID： DCS-6100LH-XXXX(MAC last 4 letter)device SSID， as the image below：

（2）Click and connect DCS-6100LH-XXXX SSID and enter the wi-fi password on the label at the device bottom

（3）Visit http://182.168.0.20 by Chrome browser after you connect to device's SSID

（4）Click "Select file" and select firmware file

（4）Click "update"

(5) There is a countdown timer for 120s during upgrade progress

(6) Please unplug/plug power after web pop-up upgrade success then the upgrade progress is finished。