



POWERLINE HD ETHERNET ADAPTER

INTERNET VIDEO, VOICE OVER ELECTRICAL WIRES

Up to 200Mbps speed,¹ suitable for video/voice distribution, broadband Internet over home's electrical wires



QUALITY OF SERVICE

Prioritized traffic for streaming video, on-line games, Internet phone, music



TOTAL SECURITY

Data encryption/Net ID to keep out intruders in building, VLAN isolation to protect home network from being tapped



200Mbps TRANSMISSION OVER ELECTRICAL WIRES 1

The D-Link DHP-300 Powerline HD Ethernet adapter is a new-generation power line network that provides easy-to-use technology for high-quality transfers of Internet video, music, games and voice through the conventional home power sockets. Delivering data transfer rates of up to 200Mbps, this adapter provides ample network bandwidth, enabling digital home consumers to tap into the existing electrical wiring for extension of their home network.¹

IDEAL FOR HD VIDEO, MUSIC SHARING, ON-LINE GAMES

The DHP-300 is ideal for connecting home network entertainment components normally located near a power outlet. Any Ethernet-ready devices, such as broadband routers, computers, High Definition TV, digital video recorders, game consoles, print servers or D-Link Media Players can be added to a home network. This adapter is ideally suited for next generation home applications such as media streaming, music sharing and online multi-player gaming. The DHP-300 can be used to stream data into areas of a home where it may be difficult to run an Ethernet cable. For wireless application, users can also expand a Wi-Fi network at home by connecting an access point to this adapter to get stronger wireless signals in remote areas such as a basement.

SMOOTH AND SECURE OPERATION

With QoS support, application priority levels are retained. This adapter ensures video, Internet phone and on-line games don't experience glitches while a file download or web surfing is taking place. It provides user-configurable data encryption and VLAN Tagging to protect a home network from wire tapping by intruders in the same building.

SIMPLE PLUG AND PLAY

The DHP-300 adapter plugs straight into a wall outlet, with no additional power cord required. No new cables or wires are needed to install a network that takes advantage of ordinary AC power and the ever-present wall sockets. And the electrical current doesn't interfere with the data network because electricity and data are transmitted at very different frequencies.

WHAT THIS PRODUCT DOES

With up to 200Mbps network data transfer rate, the

DHP-300 allows you to network your home computers, High-Definition TV, networking devices and gaming devices through the most pervasive medium in your house - the electric power lines - and share Internet connections, printers, transfer files, play games, and more.¹ This Powerline HD Ethernet adapter features plug-and-play installation, and can be attached to any DHP-300

Dink


Power Prongs (Country Dependent) ²
To AC Wall Outlet

device equipped with an Ethernet interface.

FAST TRANSMISSION ON HOME POWERLINE

The DHP-300 Powerline HD Ethernet adapter uses the latest technology to deliver up to 200Mbps wired speed over a premise's existing electrical wires.\(^1\) This fast transmission speed provides ample bandwidth to stream high-quality video HDTV signals, while simultaneously providing high-speed Internet access throughout an entire home. With QoS support, this adapter does not compromise applications with real-time requirements, such as VoIP Internet phone and multiplayer on-line games, while allowing you to enjoy Internet TV and music in your living room.

YOUR NETWORK SETUP



RJ-45 10/100BASE-TX Ethernet Ports

To TV Set-Top Box, Computers, Game Console, Network StorageDavice, Media player

TECHNICAL SPECIFICATIONS

STANDARD

IEEE 802.3 Ethernet/ 802.3u Fast Ethernet

POWER LINE INTERFACE

- + Power prongs
- + Prong type: country-dependent

ETHERNET INTERFACE

- + Port: 10/100BASE-TX with auto MDI/ MDIX
- + Connector: RJ-45

POWER LINE MODULATION SCHEME OFDM Symbol Modulation

POWER LINE FREQUENCY BAND 2MHz to 32MHz

DATA RATE

- + Power Line: 200Mbps (PHY rate)
- + Ethernet: 10/100Mbps (autonegotiation)

QoS

- + 802.1P Priority Queues standard (4 queues)
- + Multi segment bursting

SECURITY

- + Mixed DES/3DES data encryption
- + User-configurable Net ID (data encryption key)
- + 802.10 VLAN Tagging

CONFIGURATION/MANAGEMENT

- + Windows-based Utility Program
- + SNMP support (to manage encryption key)
- + Telnet
- Remote software upgrade (FTP-based)

MINIMUM SYSTEM REQUIREMENTS (To run Utility Program)

- + PC with 233MHz processor
- + 64MB memory
- + Windows XP SP2 or 2000 SP4
- + Ethernet adapter (100Mbps)

DIAGNOSTIC LED

- + Power Line Link
- + Power Line Activity
- + Ethernet Link/ Activity

AC INPUT

100 to 240VAC, 50/60Hz, 160mA

DIMENSIONS

101 x 71 x 37 mm (3.98 x 2.79 x 1.46 inches)

WEIGHT

172 grams (0.379 lb)

OPERATION TEMPERATURE

 0° to $40^{\circ}C$ (32° to $104^{\circ}F$)

STORAGE TEMPERATURE

-20° to 70°C (-4° to 158°F)

OPERATION HUMIDITY

10% to 95% RH non-condensing

STORAGE HUMIDITY

10 to 90% RH non-condensing

ЕМС

- + FCC Part 15 Class B
- + CE

SAFETY

UL

MTBF

100,000 hours or higher



- 1 Maximum wired signal rate. Actual data throughput will vary. Network conditions, including volume of network traffic and network overheads, can lower actual data throughput rate.
- ² Power prongs can differ, depending on the country to which the product is shipped.

D-Link Worldwide Offices USATFI: 1-800-326-1688 FAX: 1-866-743-4905 Snain TFI: 34 93 409 0770 FAX: 34 93 491 079 TFI: 90-212-289-5659 FAX: 90-212-289-7606 Iran TEL: 92-21-454-8158 Canada . Portuga FAX: 92-21-453-5103 Europe (U. K.) TEL: 44-20-8955-9000 FAX: 44-20-8955-9001 Greece TEL: 30 210 9914 512 FAX: 30 210 9916902 Israel TEL: 972-9-9715700 FAX: 972-9-9715601 TEL: 49-6196-77990 Czech Republio TEL: 420 224 247 500 Latin America Germany France TEL: 33 1 30 23 86 88 FAX: 33 1 30 23 86 89 Hungary TEL: 36 (0)1 461 30 00 FAX: 36 (0)1 461 30 04 Brazil TEL: 55-11-2185-9300 FAX: 55-11-2185-9322 TEL: 31-10-282-1445 FAX: 31-10-282-1331 TEL: 48 (0)22 583 92 75 FAX: 48 (0)22 583 92 76 TEL: 27-12-665-2165 FAX: 27-12-665-2186 TEL: 32 (0)2 517 7111 Belgium & Luxemburg FAX: 32 (0)2 517 6500 Bulgaria TEL: 359 2 958 22 42 FAX: 359 2 958 65 57 Russia TEL: 7-495-744-0099 FAX: 7-495-744-0099 TEL: 41 (0)1 832 11 00 FAX: 41 (0)1 832 11 01 TEL: 40(0)21 320 23 05 FAX: 40(0)21 320 23 07 TEL: 81-3-5781-0963 FAX: 81-3-5781-0965 Austria TEL: 43 (0)1 240 27 270 FAX: 43 (0)1 240 27 271 Singapore TEL: 65-6774-6233 FAX: 65-6774-63225 Korea TEL: 82-2-890-5491 FAX: 82-2-890-549 TEL: 46 (0)8 564 619 00 TEL: 45-43-969040 FAX: 46 (0)8 564 619 01 FAX: 45-43-424347 TEL: 61-2-8899-1800 TEL: 91-22-2652 6696 FAX: 61-2-8899-1868 FAX: 91-22-2652 8914 Sweden Australia China TFI: 86-10-58635800 FAX: 86-10-58635799 TEL: 886-2-6600-0123 FAX: 886-2-6600-3939 Denmark Taiwan TEL: 47 99 300 100 FAX: 47 22 30 90 85 Middle Fast (Duhai) TEL: 971-4-391-6480 FΔ X· 971-4-390-8881 TEL: 886-2-6600-0123 FΔX-886-2-6600-9898 Headquarters FAX: 358-10 309 8841 TEL: 202-291-9035 Finland TEL: 358-10 309 8840 Egypt Italy TEL: 39-02-2900-0676 FAX: 39-02-2900-1723 Turkey TEL: 90-212-289-5659 FAX: 90-212-289-7606